USER MANUAL



Color Television

27MT3305/17



Thank you for choosing Magnavox.

Need help fast?

Read your Quick Use Guide and/or Owner's Manual first for quick tips that make using your Magnavox product more enjoyable.

If you have read your instructions and still need assistance, you may access our online help at

www.usasupport.magnavox.com or call I-800-705-2000 while with your product (and Model / Serial number)

Model No.:	
Serial No.:	

PANEL LAYOUT

MODEL PANEL **PANEL** PANEL PANEL PANEL REGISTRATION Side 1 INFORMATION 3 2 8 9 14 PANEL PANEL **PANEL PANEL** PANEL[†] **SAFETY INFO** 4 5 10 11 15 PANEL **PANEL PANEL PANEL PANEL** PANEL' 1 6 7 12 .13 16

PANEL **PANEL** PANEL PANEL **PANEL** COVER Side 2 _18 17 23 24 29 **PANEL PANEL** PANEL **PANEL PANEL** LIMITED WARRANTY 25 _26 30 19 -20 Panel Index **PANEL PANEL PANEL PANEL** PANEL¹ guq əsdneuce 21 -22 27 -28 31 Pane

Panel Index			
Subject	Panel No.	Subject F	Panel No.
Antenna Basic Connection .		Sleeptimer	24
Audio/Video Connections		AutoLock™ Controls	
AV Input Jacks	4	Access Code	17
AV Output Jacks	6	Block All Channels	19
S-Video Input Jacks	5	Block Channels	18
Automcatically Programming	ΓVΙΙ	Clear All Blocked Channels	19
Basic Remote Operation		Movie Ratings	20
Basic Television Operation		Other Blocking Options	22
Cable Box Connection		TV Ratings	21
Channel Edit	12	Understanding AutoLock™	16
Closed Caption Control	23	SmartPicture™ Control	25
Format Controls	15	SmartSound™ Control	26
Language Controls	9	Sound Menu Controls	14
Limited Warranty		Troubleshooting	27
Picture Menu Controls	13	Tuner Mode	10
Remote Batteries	3		

Remote Control Button Descriptions .7-8

Return your Warranty Registration card today to ensure you receive all the benefits you're entitled to.

Once your MAGNAVOX purchase is registered, you're eligible to receive all the privileges of owning a MAGNAVOX product. So complete and return the Warranty Registration Card enclosed with your purchase at once. And take advantage of these important benefits.

Warranty Verification

Registering your product within 10 days confirms your right to maximum protection under the terms and conditions of your MAGNAVOX warranty.

Owner Confirmation

Your completed Warranty Registration Card serves as verification of ownership in the event of product theft or loss.

Model Registration

Returning your Warranty Registration Card right away guarantees you'll receive all the information and special offers which you qualify for as the owner of your model.

Congratulations on your purchase, and welcome to the "family!"

Dear MAGNAVOX product owner:

Thank you for your confidence in MAG-NAVOX. You've selected one of the bestbuilt, best-backed products available today. We'll do everything in our power to keep you happy with your purchase for many years to come.

As a member of the MAGNAVOX "family," you're entitled to protection by one of the most comprehensive warranties and outstanding service networks in the industry. What's more, your purchase guarantees you'll receive all the information and special offers for which you qualify, plus easy access to accessories from our convenient home shopping network.

Most importantly, you can count on our uncompromising commitment to your total satisfaction.

All of this is our way of saying welcomeand thanks for investing in a MAGNAVOX product.

P.S. Remember, to get the most from your MAGNAVOX product, you must return your Warranty Registration Card within 10 days. So please mail it to us right now!

Know these **safety** symbols



This "bolt of lightning" indicates uninsulated material within your unit may cause an electrical shock. For the safety of everyone in your household, please do not remove product covering.

The "exclamation point" calls attention to features for which you should read the enclosed literature closely to prevent operating and maintenance problems.

WARNING: To reduce the risk of fire or electric shock, this apparatus should not be exposed to rain or moisture and objects filled with liquids, such as vases, should not be placed on this apparatus.

CAUTION: To prevent electric shock, match wide blade of plug to wide slot, fully insert.

ATTENTION: Pour éviter les choc électriques, introduire la lame la plus large de la fiche dans la borne correspondante de la prise et pousser jusqu'au fond.

For Customer Use

Enter below the Serial No. which is located on the rear of the cabinet. Retain this information for future reference.

Model No.	
Serial No.	

IMPORTANT SAFETY INSTRUCTIONS Read before operating equipment


- Read these instructions.
- 2. Keep these instructions.
- 3. Heed all warnings.
- 4. Follow all instructions.
- **5.** Do not use this apparatus near water.
- 6. Clean only with a dry doth.
- Do not block any of the ventilation openings. Install in accordance with the manufacturers instructions.
- Do not install near any heat sources such as radiators, heat registers, stoves, or other apparatus (including amplifiers) that produce heat.
- 9. Do not defeat the safety purpose of the polarized or grounding-type plug. A polarized plug has two blades with one wider than the other. A grounding type plug has two blades and third grounding prong. The wide blade or third prong are provided for your safety. When the provided plug does not fit into your outlet, consult an electrician for replacement of the obsolete outlet.
- 10. Protect the power cord from being walked on or pinched particularly at plugs, convenience receptacles, and the point where they exit from the apparatus.
- II. Only use attachments/accessories specified by the manufacturer.
- Use only with a cart, stand, tripod, bracket, or table specified by the manufacturer, or sold with the apparatus. When a cart is used, use caution when moving the cart/apparatus combination to avoid injury from tip-over.
- Unplug this apparatus during lightning storms or when unused for long periods of time.
- 14. Refer all servicing to qualified service personnel. Servicing is required when the apparatus has been damaged in any way, such as powersupply cord or plug is damaged, liquid has been spilled or objects have fallen into apparatus, the apparatus has been exposed to rain or moisture, does not operate normally, or has been dropped.
- 15. This product may contain lead and mercury. Disposal of these materials may be regulated due to environmental considerations. For disposal or recycling information, please contact your local authorities or the Electronic Industries Alliance: www.eiae.org
- 16. Damage Requiring Service The appliance should be serviced by qualified service personnel when:
 - A. The power supply cord or the plug has been damaged; or
 - B. Objects have fallen, or liquid has been spilled into the appliance or
 - C. The appliance has been exposed to rain; or
 - D. The appliance does not appear to operate normally or exhibits a marked change in performance, or
 - E. The appliance has been dropped, or the enclosure damaged.

Note to the CATV system installer: This reminder is provided to call the CATV system installer's attention to Article 820-40 of the NEC that provides guidelines for proper grounding and, in particular, specifies that the cable ground shall be connected to the grounding system of the building, as close to the point of cable entry as practical.

- Tilt/Stability All televisions must comply with recommended international global safety standards for tilt and stability properties of its cabinet design.
 - Do not compromise these design standards by applying excessive pull force to the front, or top, of the cabinet which could ultimately overturn the product.
 - Also, do not endanger yourself, or children, by placing electronic equipment/toys on the top of the cabinet. Such items could unsuspectingly fall from the top of the set and cause product damage and/or personal injury.
- 18. Wall or Ceiling Mounting The appliance should be mounted to a wall or ceiling only as recommended by the manufacturer.
- Power Lines An outdoor antenna should be located away from power lines.
- Outdoor Antenna Grounding If an outside antenna is connected to the receiver, be sure the antenna system is grounded so as to provide some protection against voltage surges and built up static charges.

Section 810 of the National Electric Code, ANSI/NFPA No. 70-1984, provides information with respect to proper grounding of the mast and supporting structure, grounding of the lead-in wire to an anten-adischarge unit, size of grounding connectors, location of antenna-discharge unit, connection to grounding electrodes, and requirements for the grounding electrode. See Figure below.

- 21. Object and Liquid Entry Care should be taken so that objects do not fall and liquids are not spilled into the endosure through openings.comply with recommended international global safety standards for tilt and stability properties of its cabinet design.
- Battery Usage CAUTION To prevent battery leakage that
 may result in bodily injury, property damage, or damage to the unit.
 Install all batteries correctly, with + and aligned as marked on
 the unit.
 - · Do not mix batteries (old and new or carbon and alkaline, etc.).
 - Remove batteries when the unit is not used for a long time.



BASIC ANTENNA AND CABLE CONNECTIONS


Your home's signal input might come from a single (75 ohm) round cable, a Converter Box, or from an antenna. In either case the connection to the TV is very easy.

If your Cable TV signal or Antenna signal is a round cable (75 ohm) then you're ready to connect to the TV.


If your antenna has flat twinlead wire (300 ohm), you first need to attach the antenna wires to the screws on a 300 to 75 ohm adapter. If you have a Cable Converter Box: Connect the Cable TV signal to the Cable Signal IN(put) plug on the Converter.

2 Connect the Cable TV cable or Antenna cable (or 300 to 75 ohm adapter) to the 75Ω plug on the TV. If you have a Cable Converter Box: Connect the OUT(put) plug from the Converter to the 75Ω plug on the TV.

Antenna Connection



Direct Cable Connection



HELPFUL HINT

After using the AutoProgram Control, press the CH + and – buttons to scroll through all the channels stored in the television's memory.

CABLE BOX CONNECTIONS

If your cable signal uses a cable box or decoder, follow the easy steps below to comblete the connection.

Cable Box (w/RF In/Outputs):

This connection will be mono.

- Connect the Cable Company supplied cable to the signal IN(put) plug on the back of the Cable Box.
- Using a separate round coaxial cable, connect one end to the OUT(put) (TO TV) plug on the back of the Cable Box.
- Connect the other end of the round coaxial cable to the 75Ω input on the back of the television. Screw it down finger tight.

NOTE: If applicable, set the OUTPUT CHANNEL SWITCH on the back of the cable box to CH 3 or 4. Tune the TV to the same channel and change channels at the cable box. In some cases, the cable box will automatically tune to either channel 3 or 4, change channels until the picture appears.


Cable Box (w/Audio/Video Outputs):

This connection will supply Stereo sound.


- 4 Connect the Cable Company supplied cable to the cable signal IN(put) plug on the back of the Cable Box.
- Using a RCA type Video Cable, connect one end of the cable to the Video (or ANT, your cable box may be labeled differently) Out jack on the cable box and the other end to the AVI Video Input on the TV.
- Connect one end of the Audio Left and Right Cable to the left and right Audio Out L & R jacks on the cable box. Connect the other end to the AV In Audio L & R Input jacks on the TV.

NOTE: Use the AV button on the TV remote control to tune to the AV channel for the cable box signal. Once tuned, change channels at the cable box, not the television.

Cable Box (w/RF In/Outputs):



Cable Box (w/Audio/Video Outputs):



Press the POWER button to turn the TV ON.

Note: You can also press any button on the front of the TV to turn the TV ON

Press the VOLUME + button to increase the sound level, or the VOLUME - button to lower the sound level.


Pressing both buttons at the same time will display the onscreen menu. Once in the menu, use these buttons to make adjustments or selections.

- Press the CHANNEL UP + or DOWN - button to select TV channels.
- 4 Point the remote control toward the remote sensor window on the TV when operating the TV with the remote.

REMOTE CONTROL

To load the supplied batteries into the remote:

- Remove the battery compartment lid on the back of the remote.
- 2. Place the batteries (2-AA) in the remote. Be sure the (+) and (-) ends of the batteries line up correctly (inside of case is marked.)
- 3. Reattach the battery lid.




AV (AUDIO/VIDEO) INPUT CONNECTION

The TV's audio/video input jacks are for direct picture and sound connections between the TV and a VCR (or similar device) that has audio/video output jacks. Follow the easy steps below to connect an accessory device to the AV In Input Jacks located on the back of the TV.

- Connect the VIDEO (yellow) cable to the VIDEO AV In jack on the back of the TV.
- 2 Connect the AUDIO (red and white) cables to the AUDIO (left and right) AV In jacks on the rear of the TV.
- Connect the VIDEO (yellow) cable to the VIDEO OUT jack on the back of the VCR.
- Connect the AUDIO (red and white) cables to the AUDIO (left and right) OUT jacks on the rear of the VCR.
- Turn the VCR (accessory device) and the TV ON.
- Press the CH+ or CH button on the remote control to select the AV channel. AV will appear in the upper left corner on the TV screen.
- With the VCR (or accessory device)
 ON and a prerecorded tape (CD,
 DVD, etc.) inserted, press the PLAY
 button to view the tape on the
 television.

HELPFUL HINT

All the AV channels can be selected by pressing the Channel + or – buttons.



S-VIDEO (S-VHS) INPUT CONNECTIONS

The S(uper)-Video connection on the rear of the TV can provide you with better picture detail and clarity for the playback of accessory sources such as DBS (digital broadcast satellite), DVD (digital video discs), video games, and S-VHS VCR (video cassette recorder) tapes than the normal antenna bicture connections.


NOTE: The accessory device must have an S-VIDEO OUT(put) jack in order for you to complete the connection on this page.

- Connect one end of the S-VIDEO CABLE to the S-VIDEO jack on the back of the TV. Then connect one end the AUDIO (red and white) CABLES to the AV In AUDIO L and R (left and right) jacks on the rear of the TV.
- 2 Connect other end of the S-VIDEO CABLE to the S-VHS (S-Video) OUT jack on the back of the VCR. Then connect the other ends of the AUDIO (red and white) CABLES to the AUDIO (left and right) OUT jacks on the rear of the VCR.
- Press the CH + or CH –
 buttons on the remote to scroll
 the channels until SVHS appears in
 the upper left corner of the TV
 screen.

Turn the VCR and the TV ON.

Now your ready to place a prerecorded video tape in the VCR and press the PLAY button.

NOTE: When using additional accessories, only one external source will be audible, as there is only one set of sound inputs. When S-Video (S-VHS) is used, it will dominate over the AV input.





AV (AUDIO/VIDEO) OUT(PUT) CONNECTIONS

The Audio/Video Output jacks are great for recording with a VCR or used to connect an external audio system for better sound reproduction.

AUDIO SYSTEM CONNECTION:

- Connect one end of the R(ight) and L(eft) AUDIO jacks on the TV to the R and L audio input jacks on your amplifier or sound system. Set the audio system's volume to a normal listening level.
- **Turn the TV and audio system ON.** To adjust the volume on the audio system, you will need to change the volume at the external audio system, not the television.


SECOND VCR CONNECTION:

NOTE: Refer to panel number 4 for the proper hookup of the first VCR. Follow the instructions on how to tune to the AV1 channel to view a pre-recorded tape.


The following steps allow you to connect a second VCR to record the program while your watching it.

- Connect one end of the yellow Video Cable to the AV Out VIDEO plug. Connect the other end to the VIDEO IN plug on the second VCR.
- Connect one end of the red and white Audio cable from the AV Out AUDIO L and R plugs on the TV to the AUDIO IN plugs on the VCR.
- Turn the Second VCR ON, insert a VHS tape and it's ready to record what's being viewed on the TV screen.

AUDIO SYSTEM CONNECTION:



SECOND VCR CONNECTION:



REMOTE CONTROL BUTTON DESCRIPTIONS

NUMBER Buttons

Press the Number buttons to select TV channels or to enter values in the menu. For single-digit channels, press the Number button for the channel you want. The TV will pause briefly before going to the chosen channel.

A/CH Button -

(Alternate Channel)

Press to switch between the last channel and the present channel.

STATUS/EXIT Button -

Press to see the current channel number.
Press to remove a menu.

CC Button -


Press to activate Closed Captioning. Details are on panel 23.


SLEEP Button -

Press to set the TV to turn itself off within a certain time. Details are on panel 24.

SmartSurf -

If your TV model has SmartSurf, press this button to move through the channels you have set. Details are on panel 27.





POWER button

Press to turn the TV on or off.

CH(annel) +/- Buttons

Press to scan memorized channels.

VOL(ume) +/- Buttons

Press to increase or decrease the sound.

MENU Button

Press to see the menu. Press repeatedly to return to previous menus or remove the menus.

Arrow **◆** ▶ **▲ ▼** Buttons

Press to select or adjust items in the menu. ◀ ▶ buttons can also be used to change the screen format.

MUTE Button

Press to eliminate or restore the TV sound. MUTE will appear on the TV when the sound is muted.

SMART SOUND Button

Press to choose a sound setting. Details are on panel 26.

SMART PICTURE Button

Press to choose a picture setting. Details are on panel 25.


How to Use the Language Control

For Spanish speaking TV owners an onscreen LANGUAGE option is present. With the LANGUAGE control you can set the TV's on-screen menu to be shown in English or Spanish.

- Press the MENU button on the remote control to show the on-screen menu.
- Press the CURSOR UP Λ or DOWN V buttons to scroll though the on-screen menu until the word INSTALL is highlighted.
- Press the CURSOR RIGHT > button to display the INSTALL menu features.
- Press the CURSOR UP Λ or DOWN ∨ buttons to scroll through the Install features until the word LANGUAGE is highlighted.
- Press the CURSOR RIGHT
 > button repeatedly to select
 English or Español (Spanish).
- When finished, press the STATUS/EXIT button to remove the menu from the TV's screen.

HELPFUL HINT


The Language control only makes the TV's on-screen MENU items appear in English or Spanish text. It does not change the other onscreen text features such as Closed Caption (CC) TV shows.



How to use the Tuner Mode Control

The TUNER MODE control allows you to change the TV's input signal to either ANTENNA, CABLE, or AUTO mode. It's important for the TV to know what type of signal to look for (Cable TV or an Antenna). In the AUTO mode, when the AUTO PROGRAM feature is activated, the TV will automatically choose the correct mode.

- Press the MENU button on the remote to show the on-screen menu.
- Press the CURSOR UP A or DOWN V buttons to scroll through the on-screen menu until the word INSTALL is highlighted.
- Press the CURSOR RIGHT > button to display the INSTALL menu features.
- Press CURSOR UP A or DOWN V buttons to scroll the Install features until the words TUNER MODE is highlighted.
- Press the CURSOR RIGHT > button to select either ANTENNA, CABLE, or AUTO mode.
- When finished, press the STATUS /EXIT button to remove the on-screen menu from the TV's screen.



Helpful Hints

When CABLE is selected, channels 1-125 are available.

When ANTENNA is selected, channels 2-69 are available.


When AUTO is selected, the TV will automatically set itself to the correct mode based on the type of signal it detects when the AUTO PROGRAM feature is activated.

AUTOMATICALLY PROGRAM

Your TV can automatically set itself for local area (or Cable TV) channels. This makes it easy for you to select only the TV stations in your area when the CHANNEL (+), (-) buttons are pressed.

Note: Make sure the antenna or cable signal connection has been completed before AUTO PROGRAM is activated.

- Press the MENU button on the remote to show the on-screen menu.
- Press the CURSOR UP A or DOWN V buttons to scroll through the on-screen menu until the word INSTALL is highlighted.
- Press the CURSOR RIGHT > button to display the INSTALL menu features.
- Press CURSOR UP Λ or DOWN V buttons to scroll the Install features until the words AUTO PROGRAM are highlighted.
- Press the CURSOR RIGHT > button to start the Auto Program scanning of channels. Auto Programming will store all available channels in the TV's memory then tune to the lowest available channel when done.
- When finished, press the STA-TUS /EXIT button to remove the menu from the TV's screen.



Helpful Hints

When CABLE is selected, channels I-125 are available.


When ANTENNA is selected, channels 2-69 are available.

When AUTO is selected, the TV will automatically set itself to the correct mode based on the type of signal it detects when the AUTO PROGRAM feature is activated.

CHANNEL EDIT

Channel Edit makes it easy for you to ADD or DELETE channels from the list of channels stored in the TV's memory.

- Press the MENU button on the remote control to show the on-screen menu.
- Press the CURSOR UP Λ or DOWN V buttons to scroll though the on-screen menu until the word INSTALL is highlighted.
- Press the CURSOR RIGHT > button to display the INSTALL menu features
- Press the CURSOR UP A or DOWN V buttons to scroll through the Install features until the words CHANNEL EDIT are highlighted.
- Press the CURSOR RIGHT > button to display the CHANNEL EDIT options.
- with the CHANNEL EDIT options displayed, and CHANNEL NO. highlighted; you can use the cursor buttons to scroll through all available channels that you wish to add (skipped OFF) or delete (Skipped ON) from the TV's memory. You can also use the NUMBERED buttons to go directly to a specific numbered channel that you want to add or skip. Or, you can also use the CH+ or CH- to quickly scan through the channels that have not been skipped.
- Using the CURSOR DOWN V button, scroll the menu to highlight the word SKIPPED.
- Now use the CURSOR RIGHT > to toggle between ON or OFF. If ON is selected the channels is skipped when scrolling channels with the CH+ or CH- buttons. If OFF is selected the channels is not skipped when scrolling channels with the CH+ or CH- buttons.
- When finished, press the STA-TUS/EXIT button to remove the menu from the screen.




HELPFUL HINTS

An "X" appearing in front of any channel will indicate that channel has skip on. When the CH + or CH - buttons are used, those channels will be skipped.

PICTURE MENU CONTROLS


To adjust your TV picture controls, select a channel and use the Picture Menu Controls listed below:

- BRIGHTNESS CONTROL Press the CURSOR RIGHT >
 or LEFT < buttons until the
 darkest parts of the picture are as
 bright as you prefer.
- 2 COLOR CONTROL Press the CURSOR RIGHT > or LEFT < buttons to add or eliminate color.
- PICTURE CONTROL Press the CURSOR RIGHT > or LEFT < buttons until lightest parts of the picture show good detail.
- 4 SHARPNESS CONTROL CUR-SOR RIGHT > or LEFT < buttons to improve detail in the picture.
- 5 TINT CONTROL Press the CURSOR RIGHT > or LEFT < buttons to obtain natural skin tones.
- COLOR TEMP CONTROL Press the CURSOR RIGHT >
 or LEFT < buttons to select
 NORMAL, COOL, or WARM picture
 preferences. (NORMAL will keep the
 whites, white; COOL will make the
 whites, bluish; and WARM will make
 the whites, reddish.)
- CONTRAST + CONTROL Press the CURSOR RIGHT > or
 LEFT < buttons to toggle the
 control On or OFF. The Contrast +
 control helps to "sharpen" the picture
 quality. The black portions of the picture become richer in darkness and
 the whites become brighter.



SOUND MENU CONTROLS

- To adjust your TV sound, select and use the Sound Menu Controls listed below:
- TREBLE: Press the CURSOR RIGHT > or LEFT < buttons to adjust the control. The control will enhance the high frequency sounds.
- BASS: Press the CURSOR RIGHT > or LEFT < buttons to adjust the control. The control will enhance the low frequency sounds.
- BALANCE: Press the CURSOR RIGHT > or LEFT < buttons to adjust the level of sound coming from the left and right speakers.
- AVL: (Auto Volume Leveler) Press the CURSOR RIGHT > or LEFT < buttons to turn the control On or Off. When On, AVL will level out the sound being heard when sudden changes in volume occur during commercial breaks or channel changes.
- 5 INCR. SURROUND: Press the CURSOR RIGHT > or LEFT < buttons to select between lncr. Surround or Stereo settings (If Stereo), or select Spatial or Mono (If Mono).
- SOUND: Press the CURSOR RIGHT > or LEFT < buttons to select between Stereo or Mono settings. Note: If Stereo is not present on a selected show and the TV is placed in the Stereo mode, the sound coming from the TV will remain in the Mono mode.



√ Treble	◀	 50 ▶	
✓ Bass		 50 ▶	l

✓ Balance	4 L — R ▶

√AVL	On
	or Off

✓ Incr. Surround	Spatial
	or Mono
✓ Incr. Surround	Incr. Surround
	or Stereo

✓ Sound	Mono
	or Stereo




THE 4:3 EXPAND FORMAT CONTROL

Many times while watching movies from a DVD player the image is shown in "letter box" format. This is the format that is shown in movie theaters. when shown on a TV screen, the image will have areas of black on top and bottom of the screen.

- Press the MENU button on the remote to display the on-screen menu.
- Press the CURSOR DOWN V button until the word Features is highlighted.
- Press the CURSOR RIGHT > button to display the Features menu options (Autolock or Format).
- Press the CURSOR DOWN V button until the word Format is highlighted.
- Press the CURSOR RIGHT > or LEFT < buttons to select one of the two options 4:3 or Expand 4:3.
 - **4:3** Standard format for the TV. **Expand 4:3** Enlarges the picture to fill out the entire screen area, eliminating the "letter box" effect.
- When finished, press the STATUS /EXIT button to remove the menu from the TV's screen.


Note: The Expand 4:3 format can also be activated using the CURSOR UP Λ or DOWN V buttons when the onscreen menu is not being displayed. Pressing these buttons will toggle the standard 4:3 format and the Expand 4:3 format.



✓ Format 4:3 Expand ►









Understanding AutoLock Controls

T he AutolockTM feature is an integrated circuit that receives and processes data sent by broadcasters, or other program providers, that contain program content advisories. When programmed by the viewer, a TV with AutolockTM can respond to the content advisories and block program content that may be found objectionable (such as offensive language, violence, sexual situations, etc.). This is a great feature to censor the type of viewing children may watch.

Autolock[™] offers various BLOCKING controls from which to choose:

Access Code - An Access Code must be set to prevent children from unblocking questionable or censored programming set by their parents.

Channel Block - After an access code has been programmed, you can block individual channels including the A/V inputs.

Clear All - Allows you clear all channels being blocked from your viewing set with the Channel Block Control.

Block All - Allows you to block ALL channels and A/V inputs at one time.

Movie Ratings - Certain blocking options exist which will block programming based on ratings patterned by the Motion Pictures Association of America.

TV Ratings - Just like the Movie Ratings, programs can be blocked from viewing using standard TV ratings set by TV broadcasters.

MOVIE RATINGS

G: General Audience - All ages admitted. Most parents would find this program suitable for all ages.

PG: Parental Guidance Suggested - This programming contains material that parents may find unsuitable for younger children.

PG-13: Parents Strongly Cautioned - This programming contains material that parents may find unsuitable for children under the age of 13.

MOVIE RATINGS Continued

R: Restricted - This is programming is specifically designed for adults. Anyone under the age of 17 should only view this programming with an accompanying parent or adult guardian.

NC-17: No one under the age of 17 will be admitted. This type of programming should be viewed by adults only.

X:Adults Only - This type of programming contains one or more of the following: very graphic violence, very graphic and explicit or indecent sexual acts, very coarse and intensely suggestive language.

TV RATINGS

TV-Y -- Designed for a very young audience, including children ages 2-6.

TV-Y7 -- It may be appropriate for children age 7 and above who have acquired the development skills needed to distinguish between make-believe and reality.

TV-G -- Suitable for most audiences, this type of programming contains little or no violence, no strong language, and little or no sexual dialogue or situations.

TV-PG -- This program contains material that parents may find unsuitable for younger children. Could contain Moderate violence (V), some sexual situations (S), infrequent coarse language (L), or some suggestive dialogue (D).

TV-14 -- This program contains some material that many parents would find unsuitable for children under 14 years of age. This type of programming contains one or more of the following: intense violence (V), intense sexual situations (S), strong coarse language (L), or intensely suggestive dialogue (D).

TV-MA -- This program is specifically designed to be viewed by adults and therefore may be unsuitable for children under 17. This type of programming contains one or more of the following: graphic violence (V), explicit sexual situations (S), or crude indecent language (L).


SETTING UP AN ACCESS CODE

Over the next few panels you'll learn how to block channels and get a better understanding of the rating terms for certain programming.

First, let's start by learning how to set a personal access code:

- Press the MENU button on the remote to display the on-screen menu.
- Press the CURSOR UP Λ or DOWN V buttons until the word FEATURES is highlighted.
- Press the CURSOR RIGHT > button to display the FEATURES menu options.
- Press the CURSOR UP Λ or DOWN V buttons until the words AUTOLOCK ™ are highlighted.
- Press the CURSOR RIGHT > button. The screen will read, "ACCESS CODE - - ?"
- Using the NUMBERED buttons, enter 0, 7, 1, 1. "XXXX" appears on the Access Code screen as you press the numbered buttons.
 - "INCORRECT CODE" will appear on the screen, and you will need to enter 0, 7, 1, 1 again.
- The screen will ask you to enter a "New Code." Enter a "new" 4 digit code using the NUM-BERED buttons. The screen will then ask you to CONFIRM the code you just entered. Enter your new code again. "XXXX" will appear when you enter your new code and then display the AutolockTM menu options.

Proceed to the next banel to learn more...





BLOCK CHANNELS


After your personal access code has been set (see previous page), you are now ready to select the channels or the A/V Inputs you want to block out or censor. Once you've entered your access code and the Autolock™ features are displayed on the screen:

- Press the CURSOR UP Λ or DOWN V buttons until the words BLOCK CHANNELS are highlighted.
- Press the CURSOR RIGHT > button to turn blocking ON or OFF for that channel. When ON is selected the channel will be blocked.
- Press the CH + or CH button to select other channels you wish to block. Repeat step 9 to block the new channel.
- When finished, press the STATUS/EXIT button to remove the menu from the screen.

NOTE: If you ever forget your code, the 0, 7, 1, 1 code is the factory default and can be used to enter and create a new access code.









BLOCK/CLEAR ALL CHANNELS AT THE SAME TIME

After blocking specific channels there may come a time when you want to block or clear all the channels at the same time


Once you've entered your access code and the Autolock[™] features are displayed on the screen:

- Press the CURSOR UP A or DOWN V buttons to select either CLEAR ALL or BLOCK ALL.
- If CLEAR ALL is selected, press the CURSOR RIGHT > button to clear all blocked channels. All channels will be viewable.

If BLOCK ALL is selected, press the CURSOR RIGHT > button to turn the control ON or OFF. When ON is selected, ALL available channels will be blocked from viewing.

When finished, press the STATUS/EXIT button to remove the menu from the screen.

NOTE: If you ever forget your code, the 0, 7, 1, 1 code is the factory default and can be used to enter and create a new access code.



MOVIE RATINGS


The Autolock™ feature can block programming based on the Movie Industry ratings.


Once you've entered your access code and the AutolockTM features are displayed on the screen:


- Press the CURSOR UP A or DOWN V buttons to highlight the words MOVIE RATING.
- Press the CURSOR RIGHT > button to display the MOVIE RATING options (G, PG, PG-13, R, NC17, or X).
- Press the CURSOR UP ∧ or DOWN ∨ buttons to highlight any of the Movie Rating options. When highlighted, all these options can be turned ON (which will allow blocking) or OFF (which will allow viewing).
- 4 Use the CURSOR RIGHT > button on the remote to turn the rating option ON or OFF.

When a rating level is chosen to be blocked, any higher level rating will also be blocked from viewing. (i.e.: If "R" is selected to be blocked, NC-17 and X will automatically be blocked.)

NOTE: If you ever forget your code, the 0, 7, 1, 1 code is the factory default and can be used to enter and create a new access code.








T he Autolock[™] feature can block programming based on the TV Industry ratings.

Once you've entered your access code and the Autolock™ features are displayed on the screen:

- Press the CURSOR UP ∧ or DOWN ∨ buttons to highlight the words TV RATING.
- Press the CURSOR RIGHT > button to display the TV RATING options (TV-Y, TV-Y7, TV-G, TV-PG, TV-14, or TV-MA).
- Press the CURSOR UP ∧ or DOWN ∨ buttons to highlight any of the TV Rating options. When highlighted, all these options can be turned ON (which will allow blocking) or OFF (which will allow viewing).

NOTE: Some TV RATING options also have sub-ratings. The ratings of TV-Y7, TV-PG, TV-I4, TV-MA can be customized to block V (violence), FV (fantasy violence), S (sexual situations), L (coarse language), or D (suggestive dialogue).

- Press the CURSOR RIGHT > button on the remote to turn the TV-Y or TV-G rating ON or OFF. Or, press the CURSOR RIGHT > button to enter the sub-menus for the TV-Y7,TV-PG,TV-14 or TV-MA ratings.
- If the TV-Y7, TV-PG, TV-14 or TV-MA sub-menu is accessed, **press the CURSOR UP A or DOWN V buttons** to select one of the options (Block All, V, S, L, D, or FV).
- Press the CURSOR RIGHT > button on the remote to turn the option ON or OFF.



BLOCKING OPTIONS

Autolock™ offers the viewer other blockling features as well. With these Blocking Options, the censoring can be turned ON or OFF.

Once you've entered your access code and the Autolock TM features are displayed on the screen:


- Press the CURSOR UP A or DOWN V buttons until the words BLOCKING OPTIONS are highlighted.
- Press the CURSOR RIGHT > button to display the Blocking Options (BLOCKING, UNRATED, or NO RATING) menu.

BLOCKING: Might be called the "master switch" for Autolock™. When ON, ALL blocking/censoring will take place. When OFF, ALL blocking is disabled.

UNRATED: ALL unrated programs based on the Movie Ratings or Parental (TV) Guidelines can be blocked if this feature is set to ON and the BLOCKING feature is set to OFF.

NO RATING: ALL programming with NO content advisory data can be blocked if set to ON and the BLOCK-ING feature is set to OFF.


- Press the CURSOR UP ∧ or DOWN ∨ buttons to highlight the desired feature.
- When highlighted, each feature can be turned ON or OFF using the CURSOR RIGHT > or the CURSOR LEFT < buttons on the remote.



CLOSED CAPTIONING

Closed Captioning (CC) allows you to read the voice content of television programs on the TV screen. Designed to help the hearing impaired, this feature uses onscreen "text boxes" to show dialogue and conversations while the TV program is in progress.


- Press the CC button on the remote to display the current Closed Caption setting.
- Press the CC button repeatedly to choose from the four Closed Caption options (CC Off, CCI, CC2, CC Mute).
- When finished, press the STA-TUS /EXIT button to remove the menu from the TV's screen.



SLEEPTIMER

- Your TV can be set to automatically turn itself off at a given amount of time.
- Press the SLEEP button on the remote control and the Sleep Off timer display will appear on the screen.
- Press the SLEEP button repeatedly to pick the amount of time (15, 30, 45, 60, 90, 120, 180, or 240 minutes) before the TV will turn itself off.

NOTE: An on-screen count down will appear during the last minute before the TV shuts itself off. If any button is pressed during the last minute of the countdown, the Sleeptimer setting will be cancelled.




SMARTPICTURETM

25

Whether you're watching a movie or a sporting event, your TV has automatic video control settings matched for your current program source or content.

- Press the SMART PICTURE button on the remote control. The current Auto Picture setting will be displayed on the screen.
- Press the SMART PICTURE button repeatedly to select either PERSONAL, MOVIES, SPORTS, WEAK SIGNAL, or MULTIMEDIA picture settings.

NOTE: The way you choose to set the Picture Menu Controls will become your PERSONAL setting.



MOVIES - Preset picture options for watching Video Tapes, or DVDs.

SPORTS - Preset picture options for watching sporting events.

WEAK SIGNAL - Preset picture options for watching programs where the reception is not at its best.

MULTIMEDIA - Preset picture options for use with video gaming.


SMARTS OUND™

26

The Auto Sound feature allows the listener to select between four different factory set sound options.

- Press the SMART SOUND button on the remote control. The current Auto Sound setting will appear in the middle of the screen.
- Press the SMART SOUND button repeatedly to toggle between the four settings. (PERSONAL, MUSIC, VOICE, or THEATRE)

NOTE: The way you choose to set the Sound Menu Controls will become your PERSONAL setting.



VOICE - Preset sound options for programming where heavy dialogue is present.

MUSIC - Preset sound options for musical programming where there is little dialogue.

THEATRE - Preset sound options for watching movies.

TROUBLESHOOTING

No Power

- Check the TV power cord. Unplug the TV, wait 10 seconds, then reinsert the plug into the outlet and push the POWER button again.
- · Check that the outlet is not on a wall switch.
- Be sure the fuse is not blown on the AC power strip, if one is being used.

No Picture

- Check antenna connections. Are they properly secured to the TV's ANT 75 Ω plug?
- Check the TUNER MODE control for the correct tuner setting.
- Try running the Auto Program feature to find all available channels.
- Press the AV button on the remote to make sure the correct signal source is selected (FRONT or Current Channel).

No Sound

- Check the VOLUME buttons.
- · Check the MUTE button on the remote control.
- If you're attempting to hook up auxiliary equipment, check the audio jack connections located on the front of the TV.

Remote Does Not Work

- Check the batteries. If necessary, replace them with AA Heavy Duty (Zinc Chloride) or Alkaline batteries.
- Clean the remote control and the remote control sensor window on the TV.
- Check the TV power cord. Unplug the TV, wait 10 seconds, then reinsert the plug into the outlet and push the POWER button again.
- Be sure the fuse is not blown on the AC power strip, if one is being used.
- Check to be sure the TV outlet is not on a wall switch.

TV Displays Wrong Channel or No Channels Above 13

- · Repeat channel selection.
- Add the desired channel numbers (using the CHANNEL EDIT control) into the TV's memory.
- Check to be sure the TUNER MODES are set to the CABLE option and run the Auto Program feature to find all available channels.

MAGNAVOX LIMITED WARRANTY

Ninety (90) Days Labor & One (1) Year Parts & One (1) Year Display

MAGNAVOX warrants this product against defect in material or workmanship, subject to any conditions set forth as follows:

PROOF OF PURCHASE:

You must have proof of the date of purchase to receive warranted repair on the product. A sales receipt or other document showing the product and the date that you purchased the product as well as the authorized retailer included, is considered such proof.

COVERAGE:

(If this product is determined to be defective) LABOR: For a period of ninety (90) days from the date of purchase, Magnavox will repair or replace the product, at its option, at no charge, or pay the labor charges to any Magnavox authorized service center. After the period of ninety (90) days, Magnavox will no longer be responsible for charges incurred. PARTS: For a period of one (1) year, Magnavox will supply, at no charge, new or rebuilt replacement parts in exchange for defective parts. Magnavox authorized service centers will provide removal and installation of the parts under the specified labor warranty

DISPLAY: For a period of one (I) year from the date of purchase, Magnavox will supply, at no charge, a new or rebuilt active display device in exchange for the defective display. Magnavox authorized service centers will provide removal and installation of the parts under the specified labor warranty. (PTV screens carry a thirty (30) day replacement warranty.)

EXCLÚDED FROM WARRANTY COVERAGE

Your warranty does not cover:

 Labor charges for installation or setup of the product, adjustment of customer controls on the product, and installation or repair of antenna systems outside of the product.

 Product repair and/or part replacement because of improper installation, connections to improper voltage supply, abuse, neglect, misuse, accident, unauthorized repair or other cause not within the control of Magnavox.

A product that requires modification or

adaptation to enable it to operate in any country other than the country for which it was designed, manufactured, approved and/or authorized, or repair of products damaged by these modifications.

 Damage occurring to product during shipping when improperly packaged or cost of

associated packaging.

 Product lost in shipment and no signature verification of receipt can be provided.

 A product used for commercial or institutional purposes (including but not limited to rental purposes).

Products sold AS IS or RENEWED.

TO OBTAIN WARRANTY SERVICE IN THE U.S.A., PUERTO RICO, OR U.S. VIRGIN ISLANDS...

Contact Magnavox Customer Care Center at: I-800-705-2000

TO OBTAIN WARRANTY SERVICE IN CANADA...

1-800-661-6162 (French Speaking) 1-800-705-2000 (English or Spanish

Speaking)
REPAIR OR REPLACEMENT AS PROVIDED
UNDER THIS WARRANTY IS THE EXCLUSIVE REMEDY FOR THE CONSUMER. MAGNAVOX SHALL NOT BE LIABLE FOR ANY
INCIDENTAL OR CONSEQUENTIAL
DAMAGES FOR BREACH OF ANY
EXPRESS OR IMPLIED WARRANTY ON
THIS PRODUCT. EXCEPT TO THE EXTENT
PROHIBITED BY APPLICABLE LAW, ANY
IMPLIED WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE ON THIS PRODUCT IS
LIMITED IN DURATION TO THE DURATION OF THIS WARRANTY.

Some states do not allow the exclusions or limitation of incidental or consequential damages, or allow limitations on how long an implied warranty lasts, so the above limitations or exclusions may not apply to you. In addition, if you enter into a service contract agreement with the MAGNAVOX partnership within ninety (90) days of the date of sale, the limitation on how long an implied warranty lasts does not apply.

This warranty gives you specific legal rights. You may have other rights which vary from state/province to state/province.

Notes

Notes